



Description


JMT P-channel Enhancement Mode Power MOSFET

Features


- $V_{DS} = -30V$, $I_D = -4.2A$
 $R_{DS(ON)} < 60m\Omega$ @ $V_{GS} = -10V$
 $R_{DS(ON)} < 78m\Omega$ @ $V_{GS} = -4.5V$
 $R_{DS(ON)} < 112m\Omega$ @ $V_{GS} = -2.5V$
- Advanced Trench Technology
- Excellent $R_{DS(ON)}$ and Low Gate Charge
- Lead free product is acquired

Application


- PWM Applications
- Load Switch
- Power Management



SOT-23-3L top view



Marking and pin Assignment



Schematic Diagram

Package Marking and Ordering Information

Device Marking	Device	OUTLINE	Device Package	Reel Size	Reel (PCS)	Per Carton (PCS)
3401	JMTJ3401A	TAPING	SOT-23-3L	7inch	3000	180000

Absolute Maximum Ratings ($T_A=25^\circ C$ unless otherwise specified)

Symbol	Parameter		Max.	Units
V_{DSS}	Drain-Source Voltage		-30	V
V_{GSS}	Gate-Source Voltage		± 12	V
I_D	Continuous Drain Current	$T_A = 25^\circ C$	-4.2	A
		$T_A = 100^\circ C$	-2.7	A
I_{DM}	Pulsed Drain Current ^{note1}		-30	A
P_D	Power Dissipation	$T_A = 25^\circ C$	1.7	W
$R_{\theta JA}$	Thermal Resistance, Junction to Ambient		76.2	$^\circ C/W$
T_J, T_{STG}	Operating and Storage Temperature Range		-55 to +150	$^\circ C$

**Electrical Characteristics** ($T_J=25^\circ\text{C}$ unless otherwise specified)

Symbol	Parameter	Test Condition	Min.	Typ.	Max.	Units
Off Characteristic						
$V_{(\text{BR})\text{DSS}}$	Drain-Source Breakdown Voltage	$V_{GS}=0\text{V}$, $I_D = -250\mu\text{A}$	-30	-	-	V
I_{DSS}	Zero Gate Voltage Drain Current	$V_{DS} = -30\text{V}$, $V_{GS}=0\text{V}$,	-	-	-1	μA
I_{GSS}	Gate to Body Leakage Current	$V_{DS}=0\text{V}$, $V_{GS}= \pm 12\text{V}$	-	-	± 100	nA
On Characteristics						
$V_{GS(\text{th})}$	Gate Threshold Voltage	$V_{DS}=V_{GS}$, $I_D = -250\mu\text{A}$	-0.6	-0.9	-1.3	V
$R_{DS(\text{on})}$	Static Drain-Source on-Resistance note2	$V_{GS} = -10\text{V}$, $I_D = -4\text{A}$	-	48	60	mΩ
		$V_{GS} = -4.5\text{V}$, $I_D = -3\text{A}$	-	57	78	
		$V_{GS} = -2.5\text{V}$, $I_D = -1\text{A}$	-	77	112	
Dynamic Characteristics						
C_{iss}	Input Capacitance	$V_{DS} = -15\text{V}$, $V_{GS}=0\text{V}$, $f=1.0\text{MHz}$	-	880	-	pF
C_{oss}	Output Capacitance		-	105	-	pF
C_{rss}	Reverse Transfer Capacitance		-	65	-	pF
Q_g	Total Gate Charge	$V_{DS} = -15\text{V}$, $I_D = -4.2\text{A}$, $V_{GS} = -10\text{V}$	-	8.5	-	nC
Q_{gs}	Gate-Source Charge		-	1.8	-	nC
Q_{gd}	Gate-Drain("Miller") Charge		-	2.7	-	nC
Switching Characteristics						
$t_{d(on)}$	Turn-on Delay Time	$V_{DD} = -15\text{V}$, $I_D = -1\text{A}$, $V_{GS} = -10\text{V}$, $R_{\text{GEN}}=2.5\Omega$	-	7	-	ns
t_r	Turn-on Rise Time		-	3	-	ns
$t_{d(off)}$	Turn-off Delay Time		-	20	-	ns
t_f	Turn-off Fall Time		-	12	-	ns
Drain-Source Diode Characteristics and Maximum Ratings						
I_s	Maximum Continuous Drain to Source Diode Forward Current	-	-	-4.2	A	
I_{SM}	Maximum Pulsed Drain to Source Diode Forward Current	-	-	-30	A	
V_{SD}	Drain to Source Diode Forward Voltage	$V_{GS}=0\text{V}$, $I_s = -4.2\text{A}$	-	-0.8	-1.2	V

Notes:1. Repetitive Rating: Pulse Width Limited by Maximum Junction Temperature

2. Pulse Test: Pulse Width $\leq 300\mu\text{s}$, Duty Cycle $\leq 2\%$

Typical Performance Characteristics

Figure 1: Output Characteristics




Figure 3: On-resistance vs. Drain Current




Figure 5: Gate Charge Characteristics




Figure 2: Typical Transfer Characteristics




Figure 4: Body Diode Characteristics




Figure 6: Capacitance Characteristics




Figure 7: Normalized Breakdown Voltage vs. Junction Temperature




Figure 8: Normalized on Resistance vs. Junction Temperature




Figure 9: Maximum Safe Operating Area




Figure 10: Maximum Continuous Drain Current vs. Ambient Temperature







Figure 11: Maximum Effective Transient Thermal Impedance, Junction-to-Ambient





Test Circuit



Gate Charge Test Circuit & Waveform





Resistive Switching Test Circuit & Waveforms




Unclamped Inductive Switching (UIS) Test Circuit & Waveforms



Diode Recovery Test Circuit & Waveforms



Package Mechanical Data-SOT-23-3L



A	2.90 ± 0.1	E	0.950	J	7°	N	$0.15^{+0.03}$
B	0.4 ± 0.01	G	2.85 ± 0.1	K	1.550 ± 0.1	L	
C	2.80 ± 0.20	H	1.10 ± 0.1	M	0.40	N	
D	1.60 ± 0.1	I	0.70 ± 0.1				0.05 ± 0.03

Information furnished in this document is believed to be accurate and reliable. However, Jiangsu JieJie Microelectronics Co.,Ltd assumes no responsibility for the consequences of use without consideration for such information nor use beyond it.

Information mentioned in this document is subject to change without notice, apart from that when an agreement is signed, Jiangsu JieJie complies with the agreement.

Products and information provided in this document have no infringement of patents. Jiangsu JieJie assumes no responsibility for any infringement of other rights of third parties which may result from the use of such products and information.

 is a registered trademark of Jiangsu JieJie Microelectronics Co.,Ltd.
Copyright ©2019 Jiangsu JieJie Microelectronics Co.,Ltd. Printed All rights reserved.